PACKING LIST

Name	Quantity	Notes
Main Machine	1	
Power Cord	1	
Subdued Light Board	1	
Backup Battery Supply Line	1	
User Manual	1	

GVM

GREAT VIDEO MAKER

GVM Official website | Facebook | Download APP IOS | Download APP Android

Contact us:
support@gvm-group.com
service@gvm-group.com
sales@gvm-group.com
service-usa@gvm-group.com
service-europe@gvm-group.com
service-japan@gvm-group.com

GVM-LT-505 / GVM-LT-1005

CONTENTS

Product introduction ..... Page 1
Disclaimers ..... Page 2
Precautions ..... Page 2
GVM-LT-505 Product parameter ..... Page 3
GVM-LT-1005 Product parameter ..... Page 4
Product structure analysis ..... Page 5
Installation method ..... Page 6-8
Description of product control keys ..... Page 9
Function introduction and instruction for use ..... Page 10-14
APP control and APP on-line control ..... Page 15-17
Use and preservation ..... Page 18
Simple faults and troubleshooting ..... Page 19
Packing list ..... Page 14

PRODUCT INTRODUCTION

Welcome to "Lens light system". This product is specially designed for senior photography lovers. It has the function of "Lens light system" + "Subdued light" double photography, etc. It can also be used for YouTube video shooting. The main features are as follows:

1) Stepless adjustable dual-color temperature (color temperature and the color temperature range is 3200K ~ 5600K, Ha 144 LED beads, helps to reduce and avoid the color of the object. It is equipped with high-quality lens and has strong focusing ability, providing you with natural and vivid shooting effect.

2) APP intelligent control system, which can be controlled by your smart mobile phone.

3) Equipped with visible fan for heat cooling.

4) It has LCD screen and stepless system, achieving 360° rotation, with four level buffer, to control the light effectively, consisting of subdued light, custom control the light, in order to get the desired results in a casual way.

We believe that every using our product correctly, you can make huge progress when shooting. Before using the product, you are strongly recommended to read the instructions below carefully.

DISCLAIMERS

1. Before using this product, please read the instructions carefully and make sure you the protocol correctly. If you don't notice the instructions and warnings, you may be at risk of injury or damage to the product. We assume no liability for damage to product and other through misuse.

2. Once you use this product, you are deemed to have read the disclaimer and warning statements and understand the contents of the instructions and agree to be bound by them. The user shall bear all the consequences and responsibilities for the use of this product and complete responsibility.

PRECAUTIONS

1. Please use the matching power adapter or lithium battery with the same specifications and parameters. Do not use other power adapter with different output voltage parameters.

2. The product is not waterproof, please use it in a dry and ventilated environment.

3. The product is not anti-corrosion, please do not touch the product with any corrosive liquid.

4. When using the product, make sure the product is put firmly and prevent from falling and damage.

5. If the product will not be used for a long time, please switch off the power to reduce energy loss.

GVM-LT-505 PRODUCT PARAMETER

- Product model : GVM-LT-505
- Brand : GVM
- Product Name : Photography lights
- Product Type : Photo Studio Light Kit
- Features / Features : APP , pivot control , High color rendering index
- Color rendering index : 097
- Color temperature : 3200K~5600K
- Light output range : 3200K: 1000lux/1m
- Light adjustment method : Stepless adjustment
- Lamp beads quantity : 144
- Product Weight : 2.2KG
- Product Size (mm) : 400*230*70
- Cooling : Fan+heat-conducting heat dissipation
- Product material : Plastic
- Power : 100W
- Voltage : AC 100-240V/50/ 1Hz
- Power supply : DC12V/4A
- Power supply mode : Adapter&Battery
- Battery capacity : No battery provided
- Commonly origin : China, Huizhou

GVM-LT-1005 PRODUCT PARAMETER

- Product model : GVM-LT-1005
- Brand : GVM
- Product Name : Photography lights
- Product Type : Photo Studio Light Kit
- Features / Features : APP , pivot control , High color rendering index
- Color rendering index : 097
- Color temperature : 3200K~5600K
- Light output range : 3200K: 3000lux/1m
- Light adjustment method : Stepless adjustment
- Lamp beads quantity : 144
- Product Weight : 3.2KG
- Product Size (mm) : 400*230*70
- Cooling : Fan+heat-conducting heat dissipation
- Product material : Plastic
- Power : 150W
- Voltage : AC 100-240V/50/ 1Hz
- Power supply : DC12V/6A
- Power supply mode : Adapter&Battery
- Battery capacity : No battery provided
- Commonly origin : China, Huizhou

PRODUCT STRUCTURE ANALYSIS

INSTALLATION METHOD

1) The lamp can be installed and fixed on the bracket by rotating the knob clockwise, and unfastened by rotating it the counterclockwise direction.

2) Insert the Subdued light board from the top of the light panel.

3) Loosen the adjustment knob on both sides of the U-bracket, adjust the angle of the panel you need, and then tighten the adjustment knobs on both sides of the U-bracket.

4) There are two power supply modes to choose from:
① Plug in the battery and adapter. Plug in the adapter power cord for power supply.
② Plug in the battery, connect the adapter and the DC 5.5*2.1mm of the battery supply connection line, and turn on the battery to supply power.

Connect the lamp after inserting the battery

DESCRIPTION OF PRODUCT CONTROL KEYS

FUNCTION INSTRUCTION & INSTRUCTION FOR USE

① Mode selection :
The mode is divided into master mode and slave mode. Tap the mode key to select (switch master mode/ slave mode).
② Adjust color temperature : Adjust the color temperature and channel through knob and buttons, and can also control APP. These parameters are adjustable and can be controlled through APP, and slave computers of the same channel can also be adjusted synchronously.
MODE Grid : Brightness and color temperature cannot be adjusted, only channel values can be set.
③ Keyboard lock :
Mode Grid : Brightness and color temperature cannot be adjusted, only channel values can be set.
④ Adjust brightness (99%): range 1%~99%
Mode Grid: WiFi connection and disconnect interface.
Channel selection and automation key: adjust channel (+/-)
⑤ Adjust color temperature (CT): range 3200K~5600K
In the local mode, brightness can be adjusted by rotating brightness level knob of APP.
⑥ Indicator light
Mode Grid : when the brightness is adjusted by brightness level knob or APP, the brightness indicator light is on and the color temperature indicator light is on when the color temperature is adjusted. When the color temperature adjusting knob or APP, the color temperature indicator will

be on and the brightness indicator will be off.
Mode Grid : Color temperature indicator and brightness indicator are always on.
⑦ On-line control (Jiaxin control between lamps and lamps)
Whenever more than two photographing lights, set one to the master mode, set the rest to the slave mode, and set the channel of the master / slave through the app / control key. When the channel of the master and slave are the same, the brightness and color temperature of the frame in the same channel can be adjusted synchronously by adjusting the brightness and color temperature knobs of the master.

APP CONTROL AND APP ON-LINE CONTROL

Download and install the "Photography Lights" APP from the mobile phone App Store.

Tips: Read the "Photography lights" (commonly) on local mode when power on, enter "Jiaxin SERIES" APP on the mobile phone (bluetooth on) or WiFi on the phone), in the main menu, in the APP, (switch the devices - select "single" and select "photography light" then in the main page in APP— select "switch WiFi", and connect photography lights WiFi (password: 12345678) (Wait for about 10 seconds) (if it is successfully connected GOOD_LIGHT), return back to the main interface, after it shows "Mode Grid: temperature LED light (successfully connected)" in the main interface, it is allowed to control the lightness, color temperature, channel value in advance or and off through the control key in APP, and also the slave frame.

main menu

WiFi username and password resetting

It is able to reset the WiFi username and password if long press the WiFi reset button for 5 seconds. After resetting, the username and the password will return to the initial: WiFi username: GVM, LED: WiFi password: gvm_admin.

Bluetooth

Turn on the bluetooth on the phone App, Find and add GVM-Mesh Mesh and pair it.

Remote control

Turn on the remote control, and the phone can be controlled by the Cellular Data, Connect to the Internet, and the phone can be controlled remotely.

Reporting : If there is fault or performance degradation, do not unpack the lamp and quickly contact the seller and take the lamp and the phone. When the lamp is fault, do not hesitate to contact us, and we will do our best to deal the problem.

Warranty : Warranty period is 12 months from the date of purchase, and the lamp is subject to the warranty card.

Guarantee : Do not modify the product, or you will lose the right of maintenance.

USE AND PRESERVATION

Do not put the product in highly humid, strong electromagnetic field, direct sunlight, high temperature environment. Avoid use the product for a long time. Disconnect the power and take out the battery.

Wipe the lens, remove the power plug, dirt and dust with rather than any detergent or solvent liquid, according of damaging the surface layer.

Do not use the product in the following environments: Dust, Corrosive Gas, Corrosive Liquid, Salt Spray, Acid Rain, Alkali Rain.

Repairing : If there is fault or performance degradation, do not unpack the lamp and quickly contact the seller and take the lamp and the phone. When the lamp is fault, do not hesitate to contact us, and we will do our best to deal the problem.

Warranty : Warranty period is 12 months from the date of purchase, and the lamp is subject to the warranty card.

Guarantee : Do not modify the product, or you will lose the right of maintenance.

SIMPLE FAULTS AND TROUBLESHOOTING

Phenomenon	Check the reasons	Troubleshooting
The switch indicator does not light up.	① Check the matching power adapter indicator lights up or not.	Make sure the adapter power cord is connected to the power supply.
The lack of lightness and color temperature are out of control.	② Wrong pairing between battery, main lamp and the "Type protection"	Change the battery or optical coupler.
The current and voltage of the adapter are not matching.	Check if the mobile device and APP are connected to the lamp.	Press the "RESET" button for more seconds. Restart the APP and the mobile device.
Check if the product is "current off" because of the WiFi of mobile phone.	Bluetooth and WiFi	Turn off the Bluetooth and WiFi function of the mobile phone.