140mm

180mm

The products and materials described in this manual will be changed at any time due to technical upgrades. The company reserves the that right to change and supply the contents of the manual.

01 02

ALLPOWERS

Portable Power Station

Model:AP-SS-011

(ALLPOWERS R4000)

CONTENTS

1. Safety Instructions - 01
2. Specifications - 01
3. User guide - 01
4. Product appearance introduction - 01
5.1 Introduction of Display (Touch) Icons - 02
5.2 Charging - 02
5.3 Discharge - 02
5.4 Charging with EV charging station - 02
5.5 Parallel power station - 02
5.6 UPS function (uninterruptible power supply) - 02
5.7 APP operation guide - 03
5.8 Cleaning - 03
5.9 Power station settings - 03
6. FAQ - 03
7. Troubleshooting - 04
8. Package Contents - 04
9. Statement - 05
10. Contact us - 05

1. Safety Instructions

This product is an power station battery, be sure to read basic precautions before using.

1. Do not use this product in a wet, oily or dusty environment.
2. To reduce the risk of injury, close monitoring is required when using this product near children.
3. Do not use your fingers into the ventilation, otherwise it may cause electric shock or other dangers.
4. Do not touch the AC interface with metal, otherwise it may cause electric shock. Do and other dangers.
5. Do not disassemble or modify the product, do not clean the product with, otherwise it may cause personal damage to the product.
6. Please do not expose the product to rain and snow.
7. It is forbidden to use the product in the environment of strong radio electricity or strong magnetic field.
8. Please use the cable specially designed for the product, the company does not assume any responsibility for the damage caused by non-compliance.
9. Do not disassemble the product at will. If the product needs service or maintenance, please find a qualified repairer.
10. Improper use, failing to excessive force may cause damage to the product.
11. When disposing of used batteries, please separate batteries of different electrochemical systems.
12. Do not use the product in a flammable and explosive environment.
13. Be sure to keep the product away from fire and heat sources.

2. Specifications

General Info

Net weight: Approximately 49kG (99lbs)
Size:740*480*255mm (29*18.9*10 in)
Battery capacity: 3600wh (40)
Battery type: LiFePO4
Brand/model: Supported
UPS: Uninterruptible power supply): Supported

Input Ports

AC input Voltage: 100V-110V/120-230V/220-240V~50/60hz ;(Max:1800W)
AC input Current: 10A/15A/13A/10A/8A ;(Max: 20A/16A/ 16A)
DC Charger Specification: 12V-28V
EV Charging Station input: 2000W Max
Solar Panel Input: 1000W Max (Max)
EV Charging Station / Solar Charger: 4000W Max

Output Ports

AC output:110 Pure Sine Wave
AC output Voltage:100V-120V/ 220V-240V~ 400HV (pure 800HV)
USB-A (5V): 5V-2.4A (12W)
USB-A Fast charge: (5V, 9V,12V, 9V,5V, 12V,1.5A) 18W
USB-C (5V): 5V-3A (15W) (Max: 5V-3A (15W) ,12V-3A (36W)
Car cigarette output: 12V-10A, 120W Max
PC output: 100V-120V 300W/ 220V-240V 300W

Battery Info

Battery type: LiFP (Lithium Iron Phosphate
Battery capacity: 3600wh (40)
Protection Cycle: Long temperature protection, Low temperature protection, Over discharge protection, Over charge protection, Overload protection, Short circuit protection, Over current protection

Environmental Operating Temperature

Charge Temperature: 0°C - 40°C (32°F - 104°F)
Discharge Temperature: -20°C - 40°C (-4°F - 104°F)
Storage Temperature: 0°C - 45°C (32°F - 113°F)
Storage humidity range: 20 - 90%

Certification

CE / UL / FBE / UKCA / FCC / ROHS / UN38.3 / MSDS

3. User guide

When the AC input current continues to be abnormally larger than 15A (100-240V) 1200-1320 input current is larger than 12A, and the overload protection function will automatically cut off the output. Please reduce the load and restart the power station. If the input current is normal, it is not recommended to go through the extension power socket. At the same time, please pay attention to whether the household fuse is tripped. If it is tripped, it is recommended to replace the fuse with a new one.

When the ambient temperature exceeds standard charging cycle of the product, ALLPOWERS will not have any charge capacity for use of other unofficially charging cables and charging equipment. Please connect directly to the wall power socket. It is not recommended to go through the extension power socket. At the same time, please pay attention to whether the household fuse is tripped. If it is tripped, it is recommended to replace the fuse with a new one.

When using the product for solar panel charging, please connect according to the user manual specifications. Before connecting the solar panel please confirm that the output voltage specification of the solar panel is within 18V. Do not exceed it, and the maximum charging power is 1000W.

5.2 Charging with EV charging station

When using the product for EV charging, please pay attention to the output voltage of the charging station is between 24-28 V. Do not exceed it, and the maximum charging power is 2000W. Please pay attention to the power consumption of the charging station. If it exceeds the rated power of the charging station, it will cause the charging to stop.

This product belongs to the TYPE-2 charging station interface. For the United States and Japan, please purchase an additional TYPE-2 to TYPE-1 connector.

5.3 Parallel power station

This R4000 power station can use one or more same R4000 in parallel to expand the power capacity. Please ensure the same model of power.

When using this product for parallel connection, please connect it according to the specifications of the user manual.

Please ensure that the device battery power consumption and their current battery power are consistent.

Please note that in the parallel state, the total maximum output power does not change, only the battery capacity and power are increased.

Please ensure the parallel power station is in the same state (all in standby, all in power output, or all in charging) to avoid damage to the product.

Users can parallelize the power station capacity as shown in the figure below.

5.7 UPS function (uninterruptible power supply)

When the power station is connected to the power grid, it can connect the power grid and the AC input port of the product through the AC charging wire, and the electrical appliances can use the AC output port of the product to work at the time. the AC power comes from the power grid, not the battery. When the power grid is interrupted, the AC output port of the product will be automatically switched to the AC output mode of the product within 10ms. At this time, the electrical appliance can be directly fed by the AC output port of the product within 10ms. The battery power of the product. If the power station has to work overload the product, please pay attention to the power consumption of the electrical appliance. If it exceeds the rated power of the product, the product will stop outputting.

ALLPOWERS 400W Solar Panel (Can be connected in series)

5.4 Solar charging

Users can charge the product by connecting solar panels in series as shown in the figure.

5.5 AC charging

The AC power of this product adopts HF-PWMS fast charging technology, and the charging power can be adjusted through the software. Supports Fast Charge Technology and Mute Mode. The maximum input of Fast Mode can reach 220-120V 15A (200-240V 10A, Max Mode 220-120V 15A, 220-240V 12A with adjusting technology to achieve mute. The default input power of custom charging is Mute Mode, and the charging power is adjustable based on the actual needs of the product.

4. Product appearance introduction

5.6 Indoor charging

When the product is used for indoor charging, please connect according to the user manual specifications. When using the AC charging port, the electrical appliances can use the AC output port of the product to work at the time. the AC power comes from the power grid, not the battery. When the power grid is interrupted, the AC output port of the product will be automatically switched to the AC output mode of the product within 10ms. At this time, the electrical appliance can be directly fed by the AC output port of the product within 10ms. The battery power of the product. If the power station has to work overload the product, please pay attention to the power consumption of the electrical appliance. If it exceeds the rated power of the product, the product will stop outputting.

5.8 Cleaning

Wipe the surface of the product with a dry cloth or a slightly moistened cloth. Do not use chemicals or corrosive substances to clean the product, and do not let the product come into contact with liquids to avoid damage to the product.

5.9 Power station settings

1. Display language setting, you can switch the interface language to Chinese, English and Japanese.
2. Operation mode setting, (1)AC-ON can be switched to 50/60Hz, (2)N-ON(N can be switched to L/N/G.
3. Operation mode setting, can be set to normal mode, the power station running in the mode of the power station, (2)UPS-ON can be set to UPS mode, the power station is in the UPS mode, (3)Timing mode, (4)Timing time, 1 hours, 2 hours, 4 hours, 8 hours, the power station will be turned off after the set time (AC/DC output less than 10W) and enter the standby state.
4. Power-off delay, turn on or off the power station control power-off mode.
5. Screen brightness, adjust the brightness of the screen.
6. Voice control settings, turn on or off the voice control function.
7. Screen saver settings, the screen will be turned off after the screen saver time set in three types: select modes, 10 seconds, 30 seconds, 1 minute.
8. WiFi settings, select the WiFi name, and enter the WiFi password.
9. Bluetooth settings, turn on or off the Bluetooth function.

5.1 Introduction of Display (Touch) Icons

6. FAQ

1. What type of battery does the product use?

This product uses high-quality lithium iron phosphate lithium(LiFePO4) battery.

2. How long does the product last after a full charge?

The actual output of this product is: 1000W for 1 hour, 500W for 2 hours, 200W for 5 hours, 100W for 10 hours, 50W for 20 hours, 20W for 50 hours, 10W for 100 hours, 5W for 200 hours, 2W for 500 hours, 1W for 1000 hours.

3. Can the product be charged while in use?

Yes, it can be used while charging.

4. How to judge the product is charging?

When charging, the LCD screen will display the remaining charging time, and the battery capacity will gradually increase, and the battery percentage has a breathing animation effect.

5. How to check the battery capacity?

When the product is in use, the LCD screen will display the battery capacity.

6. Can the product be used while charging?

When charging, please turn off the product first, and then store it at dry, ventilated place with temperature between 0°C-45°C (32°F-113°F) and humidity between 20%-90%. It is not recommended to discharge the battery to 0% and recharge to 50% during three months to prolong the service life of this product.

7. Can the product be brought on the plane?

Yes.

8 Can voltage change and discharge?

Yes, it can be used for voltage conversion and charging and discharging.

9. Is the actual output capacity of the product consistent with the target capacity in the user manual?

The data provided in the user manual is the rated capacity of the battery pack of the product. Since the product has the functions of protecting the charging and discharging process. Therefore, the actual output capacity of the product is lower than the capacity specified in the user manual, and display the battery capacity.

7. Troubleshooting

Note: Tap to enter the LCD interface for more related faults.

Indicator	Problem	Solution
USB-A overcurrent protection	USB-A overcurrent protection	Remove abnormal load and manually turn on 5V again
USB-C overcurrent protection	USB-C overcurrent protection	Remove abnormal load and manually turn on 5V again
USB-C Overcurrent	USB-C overcurrent protection	Remove abnormal load and manually turn on 5V again
USB-A overcurrent protection	USB-A overcurrent protection	Remove abnormal load and manually turn on 5V again
USB-C overcurrent protection	USB-C overcurrent protection	Remove abnormal load and manually turn on 5V again
USB-C overcurrent protection	USB-C overcurrent protection	Remove abnormal load and manually turn on 5V again
USB-C overcurrent protection	USB-C overcurrent protection	Remove abnormal load and manually turn on 5V again
The battery is overheating during charging	The temperature of the battery is too high at the time of charging	Please wait for the temperature of the product to be normal
The battery is overheating during discharging	The temperature of the battery is too high at the time of discharge	Please wait for the temperature of the product to be normal
Inverter over-power	Overload protection	Do not use equipment that exceeds the rated power
Inverter over-voltage	Overload protection	Do not use equipment that exceeds the rated power
Inverter over-power	Overload protection	Do not use equipment that exceeds the rated power
Inverter over-power	Overload protection	Do not use equipment that exceeds the rated power
Other faults in or out the fuse number	Please contact customer service for details.	

8. Package Contents

9. Statement

Before using this product, please read the user manual of this product to ensure correct use and to avoid misuse or improper use. If you do not operate the product correctly, you could cause serious injury to yourself or others, or result in product damage and property damage. Once you use the product, you will be considered to have read the entire user manual, understand all safety precautions, and accept all terms of use. The user undertakes to be responsible for his own actions and all consequences of using the product. The company is not responsible for any losses caused by the user's failure to use the product in accordance with the User Manual.

Disclaimer of liability for product upgrades and updates

Regardless of the accuracy and or relevance of the content of this manual, when the product's F/S is updated, revised or terminated without prior notice, please read the ALLPOWERS official website for the latest product information.

This product is not intended for use in applications that require extremely high reliability and safety, such as medical equipment, aviation equipment, aerospace equipment, nuclear energy equipment, and medical equipment. Please make a judgment after fully confirming the suitability of the product and the device by yourself. If the product is used in the above equipment or in other abnormal operations, the company will not provide any guarantee. We, as manufacturer of this equipment is not responsible for the failure of the product.

10. Contact us

If you have any questions or need assistance with our products and services, please contact us through the following channels:

Our official website: www.allpowers.com

03 04

ALLPOWERS

ポータル電源

Model:AP-SS-011

(ALLPOWERS R4000)

1. 安全に関する注意

1. 湿気、油分、ほこりの多い環境でこの製品を使用しないでください。
2. 小児の近くでこの製品を使用する場合は、怪我のリスクを減らすために、厳重な監視が必要です。
3. 通気口に指を入れないでください。感電やその他の危険を引き起こす可能性があります。
4. ACポートを金属で触れないでください。感電やその他の危険を引き起こす可能性があります。
5. 製品を分解または改造しないでください。製品を清掃しないでください。本来の使用以外の目的で使用すると、製品や個人の損傷を引き起こす可能性があります。
6. 製品を雨や雪にさらしないでください。
7. 強い電波や強い磁場の環境でこの製品を使用することは禁止されています。
8. 当社が指定した専用ケーブルを使用してください。当社は、ご指定のケーブルを使用しないことによって生じる損害に対する責任を負いません。
9. 製品を勝手に分解しないでください。サービスまたはメンテナンスが必要な場合は、資格のある修理者を見つけてください。
10. 過度の力を加えたり、無理に使用したりすると、製品に損傷を与えることがあります。
11. 使用済みのバッテリーを廃棄する場合は、異なる電気化学システムのバッテリーを分離してください。
12. 可燃性および爆発性の環境でこの製品を使用しないでください。
13. 製品を火や熱源から遠ざけてください。

2. 仕様

基本パラメータ

重量 約49kG
サイズ 740*480*255mm

バッテリー情報

バッテリー容量 3600wh
バッテリータイプ 磷酸鉄
バッテリーブランド/モデル ALLPOWERS
UPS機能 (無停電電源) 対応

入力ポート

AC入力電圧:100V-110V/120-230V/220-240V~50/60hz ;(Max:1800W)
AC入力電流:10A/15A/13A/10A/8A ;(Max: 20A/16A/ 16A)
DC充電仕様:12V-28V
EV充電ステーション入力:2000W Max
ソーラーパネル入力:1000W Max (Max)
EV充電ステーション/ソーラーチャージャー:4000W Max

出力ポート

AC出力:110 Pure Sine Wave
AC出力電圧:100V-120V/ 220V-240V~ 400HV (pure 800HV)
USB-A (5V): 5V-2.4A (12W)
USB-A 急速充電: (5V, 9V,12V, 9V,5V, 12V,1.5A) 18W
USB-C (5V): 5V-3A (15W) (Max: 5V-3A (15W) ,12V-3A (36W)
シガーソケット出力: 12V-10A, 最大120W
PC出力: 100V-120V 300W/ 220V-240V 300W

バッテリータイプ

リン酸鉄(LiFP (Lithium Iron Phosphate)
バッテリー容量:3600wh (40)
保護サイクル: 長温度保護、低温保護、過放電保護、過充電保護、過負荷保護、短絡保護、過電流保護

温度範囲

充電温度範囲: 0 - 40℃ 使用温度範囲: -20 - 40℃
保管温度範囲: 0 - 45℃ 相対湿度範囲: 20 - 90%

認証

CE/UL/FBE/UKCA/FCC/ROHS/UN38.3/MSDS/TELEC

3. ユーザーガイド

1. 製品のインターフェイスを長時間使用しないでください。
2. 製品を使用する前に、接続されているすべてのデバイスの電源をオフにしてください。
3. 製品を使用する前に、接続されているすべてのデバイスの電源をオフにしてください。
4. 製品を使用する前に、接続されているすべてのデバイスの電源をオフにしてください。
5. 製品を使用する前に、接続されているすべてのデバイスの電源をオフにしてください。
6. 製品を使用する前に、接続されているすべてのデバイスの電源をオフにしてください。
7. 製品を使用する前に、接続されているすべてのデバイスの電源をオフにしてください。
8. 製品を使用する前に、接続されているすべてのデバイスの電源をオフにしてください。
9. 製品を使用する前に、接続されているすべてのデバイスの電源をオフにしてください。
10. 製品を使用する前に、接続されているすべてのデバイスの電源をオフにしてください。
11. 製品を使用する前に、接続されているすべてのデバイスの電源をオフにしてください。
12. 製品を使用する前に、接続されているすべてのデバイスの電源をオフにしてください。
13. 製品を使用する前に、接続されているすべてのデバイスの電源をオフにしてください。

4. 製品外観

5.1 タッチアイコンの説明

5.2 充電

5.3 放電

5.4 EV充電ステーションからの充電

5.5 AC充電

5.6 室内充電

5.7 UPS機能(無停電電源)

5.8 クリーニング

5.9 アプリの使用

5.10 電源設定

6. FAQ

1. 製品はどのタイプのバッテリーを使用しますか?

本製品は高品質のリン酸鉄リチウム(LiFePO4)バッテリーを使用しています。

2. 満充電後、製品はどのくらいの時間使用できますか?

実際の出力は:1時間1000W、2時間500W、5時間200W、10時間100W、20時間50W、50時間20W、100時間10W、200時間5W、500時間2W、1000時間1Wです。

3. 製品は充電しながら使用できますか?

はい、充電しながら使用できます。

4. 製品が充電されていることを判断するにはどうすればよいですか?

充電中は、LCDスクリーンに残り充電時間が表示され、バッテリー容量は徐々に増加し、バッテリーパーセンタンは「呼吸」効果があります。

5. バッテリー容量をチェックするにはどうすればよいですか?

製品を使用する場合、LCDスクリーンにバッテリー容量が表示されます。

6. 製品は充電しながら使用できますか?

充電中は、まず製品の電源を切ってください。次に、製品を0°C-45°C(32°F-113°F)の温度と20%-90%の湿度の乾燥した通気性のある場所に保管してください。製品の使用寿命を延ばすために、3ヶ月ごとにバッテリーを0%まで放電し、50%まで充電することをお勧めします。

7. 製品を飛行機に持ち込めますか?

はい、持ち込めます。

8. 電圧変換や充電・放電はできますか?

はい、電圧変換や充電・放電ができます。

9. 製品の実際の出力容量は、ユーザーガイドに記載されている目標容量と一致していますか?

製品のバッテリーパックの定格容量に関するデータです。製品には充電および放電プロセスを保護する機能があります。したがって、製品の実際の出力容量は、ユーザーガイドに記載されている容量よりも低くなります。ディスプレイは製品のバッテリー容量を表示します。

7. トラブルシューティング

ご案内:タッチ操作でLCDインターフェイスに入り、関連する障害を表示します。

インジケーター	問題	解決策
USB-A過電流保護	USB-A過電流保護	異常な負荷を取り除いてから手動でUSB-Aを再オンにしてください。
USB-C過電流保護	USB-C過電流保護	異常な負荷を取り除いてから手動でUSB-Cを再オンにしてください。
USB-C過電流	USB-C過電流保護	タイプC出力過負荷保護。異常な負荷を取り除いてから手動でUSB-Cを再オンにしてください。
USB-A過電流保護	USB-A過電流保護	過電流から保護します。異常な負荷を取り除いてから手動でUSB-Aを再オンにしてください。
充電しながら温度が高すぎる	バッテリー温度が高すぎる	製品が通常の状態になるまでお待ちください。
放電しながら温度が高すぎる	バッテリー温度が高すぎる	製品が通常の状態になるまでお待ちください。
インバーター過負荷	過負荷保護	定格電力を超える機器を使用しないでください。
インバーター過電圧	過負荷保護	定格電力を超える機器を使用しないでください。
インバーター過負荷	過負荷保護	定格電力を超える機器を使用しないでください。
インバーター過負荷	過負荷保護	定格電力を超える機器を使用しないでください。
他の故障をヒューズ番号の外に出す	詳細については、カスタマーサービスにお問い合わせください。	

8. 梱包品一覧

9. 声明

ご使用前に、ご使用説明書をよくお読みになり、正しくご使用ください。誤使用や不適切な使用は、ご自身や他人に重大な怪我を引き起こす可能性があります。製品を使用した場合、ご使用説明書の全内容を読み、理解し、使用のすべての条件に同意したものとみなされます。ユーザーは、ご使用説明書に従って製品を正しくご使用いただけなかったことによる損失に対する責任を負います。

10. お問い合わせ

ご質問やサポートが必要な場合、当社の製品およびサービスに関するお問い合わせは、以下のチャンネルを通じてご連絡ください。

公式ウェブサイト: www.allpowers.com

05 06

ALLPOWERS

便携式储能系统

Model:AP-SS-011

(ALLPOWERS R4000)

1. 安全指南

1. 本产品不适用于潮湿、油腻或有灰尘的环境。
2. 儿童在本产品附近使用时需要密切监护，以减少受伤的风险。
3. 为了减少受伤风险，请勿将手指伸入通风口。
4. 请勿用金属触碰AC接口，以免发生电击。
5. 请勿拆解或改装产品，请勿清洁产品，否则可能会导致产品损坏或人身伤害。
6. 请不要让产品接触雨水和雪。
7. 禁止在强电场或强磁场环境中使用本产品。
8. 请使用专门为本产品设计的电缆，因未遵守此规定而造成的任何损失，公司不承担任何责任。
9. 请勿自行拆解产品。如需维修或保养，请联系合格的维修人员。
10. 过度使用或用力过猛可能会损坏产品。
11. 处理废旧电池时，请分别处理不同电化学系统的电池。
12. 请勿在可燃和易爆环境中使用产品。
13. 请将产品远离火源和热源。

2. 规格

基本信息

重量 约49kG
尺寸 740*480*255mm
电池容量 3600wh
电池类型 磷酸铁
品牌/型号 ALLPOWERS
UPS 不间断电源 支持

输入端口

交流输入功率 最大1800W (100-240V)
交流输入电流 10A/15A/13A/10A/8A (100-240V 50/60Hz)
太阳能输入 12-28V MPPT 最大输入 最大功率2000W
EV充电桩输入 2000W
太阳能板 / 充电器 最大输入 最大4000W

输出端口

AC 额定输出 110V (100-120V)/220-240V (50/60Hz)
USB-A 5V 2.4A (12W)
USB-A 快充 (5V, 9V,12V, 9V,5V, 12V,1.5A) 18W
USB-C 5V 3A (15W) (Max: 5V-3A (15W) ,12V-3A (36W)
车载点烟器 12V-10A, 120W Max
PC 100V-120V 300W/ 220V-240V 300W

电池规格

电池类型 LFP磷酸铁
循环寿命 3500次循环后容量80%
保护类型 高温保护、低温保护、过放保护、过充保护、过载保护、短路保护、过流保护

运行温度

充电温度范围 0 - 40℃
放电温度范围 -20 - 40℃
存储温度范围 0 - 45℃
工作湿度范围 20 - 90%

认证

CE / UL / FBE / UKCA / FCC / ROHS / UN38.3 / MSDS

3. 使用指南

1. 为了减少受伤的风险，请勿将手指伸入通风口。
2. 请勿将产品放置在潮湿、油腻或有灰尘的环境中。
3. 当在儿童附近使用此产品时，需要密切监护，以减少受伤的风险。
4. 请勿用手指触碰通风口，以免造成电击或其他危险。
5. 请勿拆解或修改产品，请勿清洁产品，否则可能会导致产品损坏或人身伤害。
6. 请勿将产品暴露在雨雪中。
7. 请勿在强电磁场或强磁场环境中使用产品。
8. 请使用专门为产品设计的电缆，因未遵守此规定而造成的任何损失，公司不承担任何责任。
9. 请勿自行拆解产品。如需维修或保养，请联系合格的维修人员。
10. 过度使用或用力过猛可能会损坏产品。
11. 处理废旧电池时，请分别处理不同电化学系统的电池。
12. 请勿在可燃和易爆环境中使用产品。
13. 请将产品远离火源和热源。

4. 产品外观

5.1 触控图标说明

5.2 充电

5.3 放电

5.4 EV充电桩充电

5.5 AC充电

5.6 室内充电

5.7 UPS功能(不间断电源)

5.8 清洁

5.9 APP操作

5.10 电源设置

6. FAQ

1. 产品使用什么电池容量?

本产品采用高品质磷酸铁锂电池。

2. 产品充满电后能使用多久?

实际输出:1小时1000W、2小时500W、5小时200W、10小时100W、20小时50W、50小时20W、100小时10W、200小时5W、500小时2W、1000小时1W。

3. 产品可以边充电边使用吗?

可以边充电边使用。

4. 如何判断产品在充电?

充电时,屏幕会显示剩余充电时间,电池容量会逐渐增加,电池百分比会呈现呼吸灯效果。

5. 如何查看电池容量?

使用产品时,屏幕会显示电池容量。

6. 产品可以边充电边使用吗?

充电时,请先关闭产品,然后将其放置在干燥、通风的室内环境中,温度为0°C-45°C(32°F-113°F),湿度为20%-90%。为延长产品使用寿命,建议每三个月将电池放电至0%并充电至50%。

7. 产品可以带上飞机吗?

可以带上飞机。

8. 可以进行电压转换吗?

可以进行电压转换和充放电。

9. 产品的实际输出容量是否与用户手册中的目标容量一致?

用户手册中提供的数据是产品电池组的额定容量。由于产品具有保护充电和放电过程的功能,因此产品的实际输出容量低于用户手册中指定的容量,并显示电池容量。

7. 故障排除

注意:点击屏幕进入LCD界面以查看相关故障。

指示灯	问题	解决方案
USB-A过流保护	USB-A过流保护	移除异常负载,手动重新开启5V输出
USB-C过流保护	USB-C过流保护	移除异常负载,手动重新开启5V输出
USB-C过流	USB-C过流保护	移除异常负载,手动重新开启5V输出
USB-A过流保护	USB-A过流保护	移除异常负载,手