



CR-960

QEEKE CR-960

Chromium
Cr 24
51.996



WWW.QEEKESTUDIO.COM


PACKING LIST

- QEEKE three-mode mechanical keyboard x 1
- Two-in-one puller x 1
- Manual x 1
- Packaging box x 1
- Coiled Cable x 1
- Product use guide card x 1
- Packaging bag x 2

CR-960 Keyboard Specifications

Number of keys: 96 keys
 Keyboard Switches: Mechanical
 Keyboard battery: 5000mAh
 Working time: 4-6 weeks (depends on lighting brightness and ways of use)
 Charging time: about 6.5 hours
 Charging port: Type-c
 Modes: Wired/Bluetooth/2.4G
 Bluetooth version: Dual-channel 3.0/5.0 optional (version displayed may vary in different devices)
 Wireless working distance: Within 10m straight
 Bluetooth name: BT3.0KB/BT5.0KB
 2.4G name: 2.4G Wireless Device
 Dimension: 396mmx141.6mmx44.52mm+1mm
 Weight: about 1080g±20g
 Software support: Apple driver/Windows driver available for downloads


Function Description



Three Modes

- 1. Bluetooth
- 2. Wired
- 3. 2.4G

Type-c Wired port/Charging Port
 (Note: Whether the battery is being activated or not, it will charge the battery when it's wired)



Light Instruction

Wireless	Position	Re-connect	Pairing	Done
BT1	Key1	Flash green slow	Flash green fast	Green light on
BT2	Key2	Flash Blueslow	Flash Bluefast	Blue light on
BT3	Key3	Flash Red slow	Flash Red fast	Red light on
2.4G	Fn+W+R	Flash yellow slow	Flash yellow fast	Yellow light on

Low power indication: Flash red, 3.3-3.1V
 Charging: Red light on. If fully charged, green light on.
 Low power then shut down: Under Wireless mode, when power is under 3.1v, the keyboard will shut down.
 If plugged in again, the keyboard will work again, or when the power is above 3.3v, the keyboard will work again.

Wired	Light position	Indicator
Low power	Unique light indicator	Flash Red fast
Charging	Unique light indicator	Red light on
Fully Charged	Unique light indicator	Green light on
Caps	Unique light indicator	White light on
Num	Unique light indicator	White light on
Win key locked	L_Win	White light on

Precautions:

- Place the accessories and packaging parts out from childrens' reach, to prevent suffocation.
- Please keep the product dry to avoid corrosion.
- Do not expose the product to extreme temperatures lower than -10 degrees Celsius or higher than 50 degrees Celsius, to maintain the life of the keyboard and battery.
- Please use original accessories provided to avoid damage to the product or accessories..

Multi-Media Keys

Windows: Brightness- Mac: Brightness-	Brightness+	Background	Start	Email	Home
Windows: Last song Mac: Last song	Pause	Next Song	Mute	Volume-	Volume+

Other Shortcut Keys

- FN + 1** = Short press to Bluetooth1, Long press 3s switch to device1
- FN + 2** = Short press to Bluetooth2, Long press 3s switch to device2
- FN + 3** = Short press to Bluetooth3, Long press 3s switch to device3
- FN + Space** = Turn on/off all lights
- FN + PrtSc** = Change backlight color: multi-colors, red, orange, yellow, green, cyan-blue, blue, purple, white
- FN + S + L** = Press for 3s switch to sleep mode, press again to resume, the backlight flashes after the switch is done
- FN + I** = Increase the brightness of the keyboard backlight
- FN + D** = Decrease the brightness of the keyboard backlight
- FN + →** = The keyboard dynamic light effect flows faster
- FN + ←** = The keyboard dynamic light effect flows slower
- FN + F + M** = Press for 3s to switch between multimedia keys and functional keys, the backlight flashes after the switch is done
- FN + W + R** = Press for 3s switch to 2.4G pairing mode. The indicator light flashes quickly, then insert the receiver, the indicator light stops flashing means the connection is done
- FN + >** = Change the direction of the keyboard lighting flashing, from left to right
- FN + <** = Change the direction of the keyboard lighting flashing, from right to left
- FN + DEL** = Backlight effects switch in cycle
- FN + O + S** = Reset to factory mode

Bluetooth Pairing

After the keyboard is turned on, toggle the switch to enter the Bluetooth mode 1, press FN+1/2/3 to enter the Bluetooth mode, long press the FN+1/2/3 key combo for 3S, the keyboard enters the pairing mode, The indicator flashe green/blue/red fast, the indicator light stays on for 2 seconds after connection, the reconnection time is 30s, the pairing time is 120s, and it goes to sleep after timeout. After the connection is successful, if no operation is performed for 10 minutes, it will automatically turn off all lights and enter power-saving mode, and then enter deep sleep after another 20 minutes.

2.4G Pairing

After the keyboard is turned on, press FN+W+R, press and hold for 3 seconds to enter the 2.4G pairing mode, plug in the receiver, the indicator light flashes yellow fast, after the pairing is successful, exit the pairing, the light stays on for 10S, the connection time is 30s, pairing time 120s, if no further input it will sleep mode. After the connection is successful, if there is no operation for 10 minutes, it will automatically turn off all lights and enter the power-saving mode. After another 20 minutes, it will enter deep sleep mode.

Sleep Mode:

The keyboard will automatically turn off the lights and enter the sleep mode after 10 minutes of no key input, and wake up by pressing any key.
 Deep sleep mode: 30 minutes (light sleep 10 minutes + another 20 minutes).

Low power

In wireless mode, when battery is lower than or equal to 3.1V, it will enter the shutdown mode, and when it is plugged in, it can resume normal use. Or when the battery is above 3.3V, it can be used normally.

Troubleshooting

- I cannot pair the keyboard with my device.**
 Answer: Make sure that the device you want to pair with has Bluetooth. Restart the device and try to pair with the keyboard again.
 Note: On Windows, new Bluetooth connections sometimes require additional software updates, after a message indicating successful completion, the process may still be in progress and wait at least 20 minutes after pairing, just to ensure that all updates are completed before restarting the computer.
 Confirm that the device configuration accepts Bluetooth connections (Windows) and supports external keyboards (HID profile)
 Go to Bluetooth device>Settings, and then select the following boxes:
 Allow Bluetooth devices to find this computer
 Allow Bluetooth devices to connect to this computer
 Remind me when the Bluetooth device wants to connect
- My keyboard cannot be used.**
 Answer: Restart the keyboard. Turn off Bluetooth and restart the computer. (Windows About device: Go to Bluetooth settings, turn off Bluetooth and forget the keyboard. Restart the device, and turn on Bluetooth to reconnect.
- Wireless connection interfered within 10 meters.**
 Answer: Check whether the keyboard is placed on a metal surface that may interfere with Bluetooth signals or around devices in the same channel (such as routers, etc.)
- Third-party input tools are not compatible with the keyboard.**
 Answer: Due to the compatibility, version, brand and driver of the Windows/Android system, third-party input tools may be affected when using the keyboard. Please make sure your operating system and driver are up to date.
- Some FN keys or multimedia keys do not work in Windows/Android mode.**
 Answer: Due to Windows/Android system compatibility, version, brand and driver, some multimedia key functions may not be used.

Product Warranty

Thank you for your trust and support for our products, in order to protect your rights and interests, our company will strictly abide by and implement relevant regulations and implement after-sales service.

- Service validity period: 12 months of quality assurance from the date of purchase
- Service content: Provide services in accordance with the regulations on the responsibility for the maintenance, replacement and return of micro products
- Not within the scope of services:
 - has exceeded the effective service or free maintenance period
 - Failure or damage caused by failure to use, maintain, or store in accordance with the correct use instructions;
 - Failure or damage caused by maintenance by a maintenance organization not authorized by our company
 - Products without dealer information and stamps on the warranty card
 - Unauthorized alteration of the contents of the Three Guarantees Certificate;
 - The product is defective due to force majeure (such as natural disasters, etc.)
 - Human factors lead to product defects (such as operating errors, bumps, improper input voltage, etc.);
 - Other failures or damages that are not caused by product design, technology, manufacturing, quality and other issues

Warranty Card

Type: _____
 Purchase Date: _____
 Name: _____
 Tel: _____
 Address: _____



QEEKE CR-960




包装清单

QEEKE 三模机械键盘 x 1 弹簧线 x 1 二合一拔键轴器 x 1 产品使用引导图示卡 x 1 说明书 x 1 包装 x 1 包装袋 x 2

CR-960键盘基础规格

按键数量: 96键
键盘轴体: 机械轴
键盘电池: 5000毫安
工作时间: 4-6周 (根据使用情况, 随亮度和使用情况而变化)
充电时长: 约6.5小时
充电接口: typec
模式: 有线/蓝牙/2.4G
蓝牙版本: 双通道3.0/5.0可选 (设备不同的情况下显示的不同)
无线工作距离: 10M以内直线距离
蓝牙设备名称: BT3.0 KB /BT5.0 KB
2.4G名称: 2.4G Wireless Device
产品尺寸: 396mmx141.6mmx44.52mm±1mm
重量: 约1080g±20g
软件支持: Windows与Mac端驱动程序提供下载, 支持AP在线更新, 支持固件更新, 桌面端软件支持全键自定义功能, Windows系统支持多媒体更改。

功能说明




三段式

- 1.上推蓝牙
- 2.中间关闭电源有线模式
- 3.下推2.4G

Mac/Win系统切换

Typec有线接口/充电接口。
(提示: 无论电池供电开启或关闭此接口
在接入状态下自动为电池充电)



指示灯说明:



无线	指示灯位置	回连	配对	连接成功
BT1	按键1灯	绿色慢闪	绿色快闪	绿光常亮
BT2	按键2灯	蓝色慢闪	蓝色快闪	蓝光常亮
BT3	按键3灯	红色慢闪	红色快闪	红光常亮
2.4G	Fn+W+R	黄灯慢闪	黄灯快闪	黄光常亮

低电指示: 指示灯快闪红灯提示低电, 3.3-3.1V报警
充电指示: 指示灯红灯常亮表示正在充电, 绿灯常亮表示已经充满。

低电关机: 无线模式下, 检测到电池低于等于3.1V时, 进入关机状态, 当插上有线充电后, 即可恢复正常使用。或者电池大于等于3.3V时, 即可正常使用。

注意事项:

请勿将本品及配件和包装部件放在儿童接触到的地方, 以防发生意外引致窒息。
请保持产品干燥, 以免腐蚀。
请勿将产品暴露在低于-10摄氏度的极端温度下, 以维持键盘和电池的使用寿命。
请使用原装配件, 以免造成产品或配件损坏。

有线	指示灯位置	指示方式
低电	独立指示灯	红灯快闪
充电	独立指示灯	红光常亮
充满	独立指示灯	绿光常亮
Caps	独立指示灯	白光常亮
Num	独立指示灯	白光常亮
锁WIN	L_Win键	白光常亮

多媒体功能

	Fn + F1	Fn + F2	Fn + F3	Fn + F4	Fn + F5	Fn + F6
Windows	亮度-	亮度+	后台	打开我的电脑	邮箱	主页
Mac	亮度-	亮度+	Mission	Launchpad	无	无

	Fn + F7	Fn + F8	Fn + F9	Fn + F10	Fn + F11	Fn + F12
Windows	上一曲	播放暂停	下一曲	静音	音量-	音量+
Mac	上一曲	播放暂停	下一曲	静音	音量-	音量+

其它快捷键操作说明

- FN + 1** = 短按切换蓝牙1, 长按3S蓝牙1设备。
- FN + 2** = 短按切换蓝牙2, 长按3S蓝牙1设备。
- FN + 3** = 短按切换蓝牙3, 长按3S蓝牙1设备。
- FN + 1** = 键盘背光亮度。
- FN + 1** = 键盘背光亮度降低。
- FN + -** = 键盘动态灯效流动速度加快。
- FN + =** = 键盘动态灯效流动速度减慢。
- FN + >** = 键盘部分灯光支持向右调节。
- FN + <** = 键盘部分灯光支持向右调节。
- FN + Space** = 开启/关闭背光灯。
- FN + DEL** = 键盘背光灯效循环切换。
- FN + PrtSc** = 主背光颜色切换 (顺序: 七彩、红、橙、黄、绿、青、蓝、紫、白)
- FN + O + S** = 复位长按3s键盘恢复出厂。
- FN + F + M** = 长按3s多媒体键与F功能键功能互换 (背光灯闪烁2次提示)。
- FN + W + R** = 切换开关到2.4G模式之后, 长按3S 2.4G配对。
- FN + S + L** = 禁用/开启休眠模式 (背光灯闪烁2次提示)。
- FN + BackSpace** = 按下组合键Fn+BackSpace, 背光灯熄灭, 数字键1到0键背灯显示电量占比。

蓝牙配对

键盘开机后, 拨动开关进入蓝牙模式1, 按下FN+1/2/3进入蓝牙模式, 长按FN+1/2/3组合键3S, 键盘进入对码状态, 绿/蓝/红色指示灯快闪, 连上后指示灯常亮2S, 回连时间30s, 配对时间120s, 超时进入休眠。连接成功, 无操作10分钟自动关闭所有灯光进入省电模式, 再过20分钟进入深睡。

休眠时间

键盘在无按键输入状态10分钟后自动关灯进入休眠状态, 按键唤醒
深睡: 30分钟 (浅睡10分钟+再过20分钟)。

2.4G配对

键盘开机后, 按下FN+W+R, 长按3秒进入2.4G强制对码模式, 插入接收器, 指示灯黄色快闪, 配对成功时退出对码, 模式灯常亮10S, 回连时间30s, 配对时间120s, 超时进入休眠。连接成功, 无操作10分钟自动关闭所有灯光进入省电模式, 再过20分钟进入深睡。

低电参数

无线模式下, 检测到电池低于等于3.1V时, 进入关机状态, 当插上有线充电后, 即可恢复正常使用。
或者电池大于等于3.3V时, 即可正常使用。

疑难排解

我无法将键盘与我的装置配对。

答: 确认您要配对的装置可使用蓝牙。
重新启动装置并再次与键盘配对。
注意: 在Windows计算机上, 新的蓝牙连接有时需要额外的软件更新-在出现表示成功完成的消息后, 该过程可能仍在进行中配对后至少等待20分钟, 以确保在重新启动计算机之前完成所有更新。
确认装置配置可接受蓝牙连接 (Windows) 并支持外部键盘 (HID配置文件)。
转到蓝牙装置>打开设置, 然后选择以下复选框:

允许蓝牙装置找到这台电脑。
允许蓝牙装置连接到这台电脑。
当蓝牙装置想要连接时提醒我。

我的键盘无法使用。

答: 关闭重新打开键盘。
关闭蓝牙重新启动计算机。
关于装置:
转到蓝牙设置并关闭蓝牙并忘记'键盘。
重启装置, 并删除原蓝牙配对。

无线连接或在10米内受干扰

答: 检查键盘是否放在可能干扰蓝牙信号的金属表面上或同信道的设备周围 (例如路由器等等)。

第三方输入工具与键盘不兼容

答: 由于Windows/Android系统的兼容性、版本、品牌和驱动程序, 第三方输入工具在使用键盘时或被影响。
请确保你的作业系统和驱动程序为最新版本。

某些FN键或多媒体键在Windows/安卓模式下不起作用

答: 由于Windows/Android系统的兼容性、版本、品牌和驱动程序, 某些多媒体键的功能可能不能被使用。

产品质保

感谢您对本公司产品的信任与支持, 为了让您放心使用本产品, 更好地保障您的权益, 我公司将严格遵守并执行相关规定, 实行售后服务。

1. 服务有效期: 自购买之日起质量保证12个月
2. 服务内容: 按微型计算机商品维修更换退货责任规定进行服务
3. 不属于服务之范围:
 - a. 已经超出有效服务或可维修范畴的;
 - b. 未按照正确使用说明使用、维护、保管导致故障或损坏的;
 - c. 非本公司授权维修机构维修导致的故障或损坏;
 - d. 无质保卡;
 - e. 擅自涂改三包凭证内容的;
 - f. 由于不可抗力(如自然灾害等)原因造成产品之不良;
 - g. 人为因素导致产品不良(如操作失误、磕碰、输入不合适电压等);
 - h. 其他非产品设计、技术、制造、质量等问题导致的故障或损坏。

质保卡

产品型号: _____
购买日期: _____
客户姓名: _____
联系电话: _____
联系地址: _____

