

折页  
成品尺寸: 85 \*125 mm

BLAVOR  
PN-W12 美国说明书

## BLAVOR Welcome Guide



PN-W12  
Qi Solar Power Bank

### Important safety instructions

**Warning:** When using this product, basic precautions should always be followed, including the following:

- Carefully read the User Manual before using the power bank.
- Close supervision is needed when the power bank is used near children.
- Do not strike, hit or insert any foreign objects into the power bank or any of its ports.
- Do not expose the power bank to heavy rain/snow to avoid malfunction.
- Do not immerge the power bank into water to avoid malfunction.
- Do not disassemble or reassemble the power bank without authorization from manufacturer
- Do not use the power bank if it has been damaged or modified. If you see any bulging, swelling, leakage or other abnormality from the power bank, stop using it immediately.

### Special Attention

- The suggested working/storage temperature is between -4°F and +140°F(-20°C~+60°C).
- Do not expose a power bank to fire or extreme high temperature.Exposure to fire or temperature above 176°F/80°C may cause battery swelling up or explosion.
- Do not leave the power bank on the car dashboard without supervision.Under hot weather, the temperature inside a parked car can reach above 176°F/80°C, where the battery may swell up or explode..

- Do not leave the power bank on the flat surface of concrete, metal and wooden floor to have the battery being solar charged. Under strong sunlight, the surface temperature of concrete,metal and wooden floor may reach above 176°F/80°C, where the battery may swell up or explode.
- For solar panel charging, we recommend that you hang the power bank in a ventilated environment for solar charging to avoid swell up of the battery due to extrem high temperature.

### Legal and Regulatory Compliance

All BLAVOR power banks have undergone extensive tests and the strict quality control procedure.Both our factory and products are tested and certified.

- ISO 9001:Quality management system that demonstrateits our ability to consistently provide products and services that meet customer and applicable statutory and regulatory requirements.
- UN38.3 Test Certificate:This ensures that the battery cell used in the power bank adheres to safety standards for things like maximum continuous charge voltage, cut off voltage, cell numbers, nominal voltage, discharge etc.
- MSDS Certificate:This is the Material Safty Data Sheet, all our power banks come with MSDS sheets, these sheets outline the hazardousness material with batteries, handling procedures, precautions etc.
- UL 2056 Test Certifictae:A safety standards proves that the products has been gone through a series of in-depth evaluations by UL expert engineers.
- CE Certifictae:All our power banks are certified with CE certificates to ensure they comply with regulations for sale in Europe Market.

### PRODUCT DETAILS

- Steady Red-Foreign Object Detection
- Steady Blue-Wireless Charging Standby Status
- Flashing Blue-5W/7.5W/10W Wireless Charging



Thank you for choosing BLAVOR Wireless Solar Charging Power Bank. Here's the instruction for your better experience.

### Product Parameters

#### 20000mAh Wireless Solar Charging Power Bank

Micro USB quick charge input port	DC 5V/2.4A 9V/2A
Type - C quick charge input/output port	DC 5V/2.4A 9V/2A
USB quick charge output port 1	DC 5V/3A 9V/2A 12V/1.5A
USB quick charge output port 2	DC 5V/3A
Wireless charging output	5W 7.5W 10W
Solar panel output	300mA (under 25000LUX)
Battery capacity	20000mAh
Battery type	polymer lithium battery
Product weight	0.5 KG

### Package Include:

- 1\*Pack BLAVOR Wireless solar power bank
- 1\*Pack USB Cable
- 1\*Pack Instruction
- 1\* Pack Carabiner
- 1\*Pack Thank-you note

### Product Specifications:

- Exclusive design, fashionable and beautiful.
- Original A-class polymer batteries, safe and stable.
- High capacity wireless portable power bank, quick charging input and output.
- Wireless charging,5W,7.5W and 10W outputs, suitable for the Qi standard products.
- Solar charging, charge your devices at any time .

### Instructions:

#### 1.Turn on/Turn off:

Gently press the power switch, then the LED battery indicators and wireless charging function are on. If there is no charging devices, power bank will automatically shut down in 30 seconds.

#### 2.How to charge the power bank:

##### Solar supply

Put the power bank under direct sunlight and sunlight will convert into electricity to charge built-in lithium battery automatically **(Strong sunlight is advised)**.

##### Power supply

Connect the TYPE-C or USB input port and wall/car adapter USB port with a cable. The blue LED indicators will be flickering while charging,and all indicators on means the power bank has been fully charged. QC3.0/ PD wall/car adaptor will quick charge the power bank.

### 3.Charge mobile phones or other devices: Cable charging

Turn on the power switch and the blue indicators are on. Plugtwo ends of the cable into the power bank USB port and the devices. QC 3.0 USB Output port and TYPE-C Bidirectional PD port support fast charging for mobile phones and devices withfast charging function.

### Wireless charging

Turn on the power switch and the wireless charging indicator in the back is on. Put your mobile phone in the wireless charging area and the charging will be on. If you normally use a protective case for your phone, please make sure that your phone case is not made of metal and the suitable thickness is less than 6mm.

### Three indicator lights below the wireless charging area

#### 1. Red Indicator Light:

Steady Red: Foreign Object Detection

#### 2. Blue Indicator Light:

Steady Blue: Wireless Charging Standby Status  
Flashing Blue: 5W/7.5W/10W Wireless Charging

### LED Flashlight Function:

Long press the power button for at least 3 seconds to turn on or turn off the flashlight.

Then, short press power button a fourth time to turn off the flashlight.

### Warning:

- This power bank is for 5V/2.4A 9V/2A devices. Devices beyond the specifications may be damaged.
- Please do not disassemble the power bank.
- Keep dry and keep away from fire. Please do not use chemicals to clean the power bank.
- Please do not charge in high temperature. Suggested temperature rang: - 4°F -140°F.
- If not intend to use the power bank for a long time, please charge it at least every three months.
- Please do not use until fully charged and do not charge mobile phones while being charged.

### Warranties and after-sales service:

- Every BLAVOR product is provided with at least 12 months of warranty and a lifelong technical support.
- Within 30 days from the date of purchase, products in good packaging and without damage can be returned and fully refunded. Please noted that customers will bear the shipping fee if products have no quality problems.
- A free exchange for products having quality problems within 12 month.
- If you are not 100% satisfied with our products, please feel free to contact our customer service at [support@blavor.com](mailto:support@blavor.com). We attach great importance to customer feedback and will get back to you within 24 hours.