

## Operation manual of LED stage lighting equipment

### Mini 4pcs \*30W COB Par Light

Parameters:

Input voltage: ac90-250v 50-60hz

Power: 120w

Light source: 4PCS\*30W , white \*2, warm white \*2

Channel: 8 ch

Control mode: DMX512, voice control, self-walking, master-slave



Please read the instruction carefully before using

## DMX 512 Channel Description

No.	Display	Function Description
1	A001	A001-512 DMX mode 8 ch
2	dI-1	dI-(1-4) Dimming curve: linear/square/inverse square /S- curve
3	Au01	Au01-15 Fixed color selection
4	FF01	FF01-99 Color jump
5	CC01	CC01-99 Color gradient
6	EE01	EE01-99 Color pulse variable
7	LL01	LL01-99 Color mutation
8	r001	r000-255 Warm white Manual dimming
9	G001	G000-255 White Manual dimming
10	b001	b000-255 Warm white Manual dimming
11	W001	W000-255 White manual dimming
12	F000	F000-255 Stroboscopic mode 1-20Hz
13	Auto	Automatic mode, repeatedly run jump/gradient/pulse/mutation
14	Sound	bLOF/bLON "OF" means silent control OF light "ON" silent control OF black field VOL1~VOL9 1-9 sensitivity adjustment

8CH:

No.	Function	Description
1CH	0-255	0-100% linear overall dimming
2CH	0-10 11-225	Strobes closed Stroboscope from slow to fast 1-20Hz
3CH	0-39 40-79 80-119 120-159 160-199 200-239 240-255	No function, the first 6 channels are valid Color jump Color gradient Color pulse variable Color mutation Automatic mode Voice control mode
4CH	0-255	Speed from slow to fast/sensitivity from small to target
5CH	0 1-255	Warm white close 0-100% linear dimming
6CH	0 1-255	White close 0-100% linear dimming
7CH	0 1-255	Warm white close 0-100% linear dimming
8CH	0 1-255	White close 0-100% linear dimming