

Sender Box

TS852D

V1.1

Jan 2018

1. Function



- 1) One DVI video signal input;
- 2) One Audio signal input;
- 3) Sending card is set by USB; can be cascaded to drive a larger screen, up to 4 cards cascaded;
- 4) Support adjusting brightness manually; three scales can be set: 16-grade, 32-grade and 64-grade;

- 5) Independent power supply;
- 6) Support 60Hz and 30Hz output mode;

2. Capability

| 60Hz mode (using two ports) | 30Hz mode (using two ports) |
|--|-----------------------------|
| 2048 × 640 | 4032 × 512 |
| 1920 × 672 | 3840 × 544 |
| 1792 × 720 | 3584 × 576 |
| 1600 × 800 | 3392 × 608 |
| 1472 × 880 | 3200 × 640 |
| 1344 × 960 | 3072 × 672 |
| 1280 × 1024 | 2880 × 704 |
| 1024 × 1280 (require supporting by graphics card) | 2560 × 800 |
| 832 × 1280 (require supporting by graphics card) | 2368 × 864 |
| 640 × 1280 (require supporting by graphics card) | 2048 × 1024 |

3. Specification

| Specifications | |
|---|----------------|
| Model | TS852D |
| Setting interface | USB |
| Input | DVI |
| Output | RJ45 |
| Net weight (contains one sending card) | 1.4KG |
| Length | 280mm |
| Width | 178mm |
| Height | 50mm |
| Input voltage | 100 ~ 240 V AC |

END