


## Hall closed loop current sensor

Sub-plate mount, terminal output. Detect DC, AC and pulse current, High insulation between primary side and the vice side circuit.



Front view



Epoxy view




Fixed hole view

### Product features


- Light weight
- Low power consumption
- Good linearity
- No insertion loss
- Fast response time
- Good anti-interference ability

### Installation diagram



### Product application

- Railway
- Metallurgical
- Welding machine
- Robot
- Motor
- Inverter power supply
- Variable frequency governor
- Uninterrupted power supply and communication power supply



**Electrical parameters:** ( The following parameters are typical values and actual values will be subject to product testing )

**Remarks:**

$I_{PN}$	Rated input	$\pm 200A$	$\pm 300A$	$\pm 300A$	$\pm 500A$	Standard input can be customized
$I_{pm}$	Input measurement range	$\pm 300A$	$\pm 450A$	$\pm 450A$	$\pm 750A$	The default is 1.5 times the rated input
$I_{out}$	Rated output	$\pm 100mA$	$\pm 100mA$	$\pm 150mA$	$\pm 100mA$	Standard output
X	Accuracy	0.5%				$I=I_{PN}$
$\epsilon L$	Linearity	0.1%				$I=0 \sim \pm I_{PN}$
$V_c$	Supply voltage	$\pm 12V / \pm 15V$				Supply voltage range $\pm 5\%$
$I_c$	Current consumption	$\pm 12mA + I_s$				Reference will be subject to the measured
$R_l$	Load impedance	-				According to the sampling voltage $V_{out} = I_{out} * R_l$
$V_{oe}$	Zero offset voltage	$\leq \pm 0.15mA$				$T_A = 25^\circ C$
$T_r$	Response time	$\leq 1 \mu s$				Reference will be subject to the measured
$N_w$	Weight	249g				Reference will be subject to the measured
$T_a$	Operation temperature	$-25 \sim +70^\circ C$				
$T_s$	Storage temperature	$-25 \sim +70^\circ C$				
$B_w$	Band width	DC $\sim$ 100KHz				Factory test according to DC
$V_d$	Dielectric strength	6KV 50Hz 1min				

### Instructions for use:

1. According to the connection mode of correct connection
2. The direction shown by the arrow is positive
3. With hole measurement, response time and following the speed for the best
4. Faulty wiring can lead to product damage and output uncertainty

### Safe operation:

- \*Please read this specification carefully before use.
- \*When you need to move the product, please be sure to disconnect the power and all the connected cables.
- \*If found shell, devices attached to the fixed parts, wire, or have any damaged, please immediately deal with hidden dangers.
- \*If there is any doubt about the safe operation of the equipment, the equipment and the corresponding accessories should be closed immediately, and the fastest time for troubleshooting.


### Proclamations:

As our products are constantly being improved and updated, we reserve the right to modify the content of this specification at any time without prior notice.


Dimensions(in mm±0.5) :

Current direction


Positive ← Epoxy surface



Front view




Side view




Bottom view

Wiring diagram (based on 0 V)



Connector Illustration:



Fast plug/seat which spacing 3.96 mm

**Terminal definition:**

- 1: +V
- 2: -V
- 3: M
- 4: N.C

※ **Detection:**

- ① Choose the auxiliary power supply with small ripple (≤10mV)
- ② Switch on auxiliary power
- ③ The auxiliary power is connected to the sensor
- ④ The sensor detects the primary current