

0605 1310 nm to 1610 nm WDM

W1006-S



1x2 Thin Film Based WDM Combiner: 1505 nm to 1515 nm/1529 nm to 1611 nm

This WDM based pump/signal combiner utilizes thin-film filter technology to combine the pump power with the input signal. It is housed in a high-power handling metal package.

FEATURES

- Low Insertion Loss
- Low PDL
- Negligible PMD
- High Stability and Reliability

USE IN

- Building Broadband
- Low-noise EDFAs
- Raman Amplifiers for Ultra-long Haul Networks

Pass Channel C ↔ P	Wavelength Range λ_p	1505 nm to 1515 nm
	Insertion Loss	0.30 dB max.
	Flatness	0.60 dB max.
	Isolation@ λ_R	40.00 dB min.
	Isolation@1487 nm	50.00 dB min.
	Isolation@1485.5 nm	55.00 dB min.
	PDL	0.10 dB max.
	Directivity P → R	55 dB min.
Reflection Channel C ↔ R	Wavelength Range λ_R	1529 nm to 1611 nm
	Insertion Loss	0.60 dB max.
	Flatness	0.15 dB max.
	Isolation@ λ_p	12 dB min.
	PDL	0.10 dB max.
	Directivity R → P@1531±2 nm	55 dB min.
Return Loss		50 dB
Fiber Type		C: SMF-28 250 micro
Connector		None
Dimension		5.5±0.2x5.5±0.2x32±2 mm
Fiber Length		1.0±0.1 m