

0605 1310 nm to 1610 nm WDM

W1028-S



1x2 Thin Film Based WDM Combiner: 1420 nm to 1443 nm/1452 nm to 1490 nm

This WDM based pump/signal combiner utilizes thin-film filter technology to combine the pump power with the input signal. It features low insertion loss, low PDL, and negligible PMD. This device is used for building broadband, low-noise EDFAs and Raman amplifiers for ultra-long haul networks. It is housed in a high-power handling metal package.

FEATURES

- Low Insertion Loss
- Low PDL
- Negligible PMD
- High Stability and Reliability

USE IN

- Building Broadband
- Low-noise EDFAs
- Raman Amplifiers for Ultra-long Haul Networks

Input Fiber [2] Wavelength	1420 nm to 1443 nm
Input Fiber [3] Wavelength	1420 nm to 1443 nm
Output Fiber [1] Wavelength	1420 nm to 1443 nm/1452 nm to 1490 nm
Insertion Loss: [1] to [3]	0.50 dB
Insertion Loss: [1] to [2]	0.50 dB
Isolation: [1] to [2] (dB)	11 dB typ.
Isolation: [1] to [3]	11 dB min.
Return Loss	50 dB min.
PDL	0.10 dB max.
Power Handling	2000 mW max.
Fiber Type	SMF-28-250 μ m
Package Dimension	6.5x6.5x80 mm