

## W6400-S

### 1310 nm/1490 nm/1550 nm FWDM

This highly reliable FWDM (filter wavelength division multiplexing) offers very low insertion loss. It can be used for transmitters and fiber lasers, WDM network system, fiberoptic instruments and fiber optical amplifier.

#### FEATURES

- Wide Operating Wavelength Range
- Low Insertion Loss
- High Channel Isolation
- Ultra Flat Wide Passband
- Epoxy-free on Optical Path

#### USE IN

- System Monitoring
- WDM Network
- Transmitters and Fiber Lasers
- Fiber Optic Instruments
- Fiber Optical Amplifier

Pass Insertion Loss	0.8 dB max.
Reflection Insertion Loss	0.6 dB max.
Pass Channel Isolation	30 dB min.
Reflection Isolation	15 dB min.
Polarization Dependent Loss	0.1 dB max.
Return Loss	50 dB min.
Wavelength Thermal Stability	0.003 nm/°C max.
Insertion Loss Thermal Stability	0.005 dB/°C max.
Channel Flatness	0.3 dB max.
Directivity	55 dB min.
Power Handling	500 mW max.
Operating Temperature	0°C to +70°C
Storage Temperature	-40°C to +85°C
Package Dimension	5.5x5.5x34 mm (L38 mm for 900 μm Loose Tube)

WDM/  
CWDM Filter

WDM/  
CWDM Filter