

Technical parameters:

Voltage: AC100-240V 50 - 60 HZ

Total power: 120W

Light source 1:6 Corey 10W four-in-one (RGBW) lamp beads

Light source 2:1 515nm green laser

Channel: 15CH

Control mode:DMX 512, master and slave, self-propelled, voice control.

X axis: 540 °

Y axis: 180 °

LED stage lighting equipment instructions.

Six bee eyes+laser



Please read the manual carefully before using it

Menu description:

Main menu	explain
Addr	A001-A512 address code
CHnd	15CH channel selection
SLnd	Running mode selection (DMX self-walking voice control)
Pset	Forward and backward setting of YES, NO Motor X
Tilt	YES, NO Motor Y forward and backward setting
SEne	Sound control sensitivity adjustment (0 -100)
LED	ON, OFF screen always bright settings
DISP	YES, NO displays forward and backward settings
Ver	V100 software version number
Faet	YES, NO restore factory settings
Fine tuning menu	Press the menu key 5S and pull out the fine tuning menu
Pan	0 -127 ,-1-127 forward and backward fine tuning
Tilt	0 -127 ,-1-127 forward and backward fine tuning
Zoom	0 -127 ,-1-127 forward and backward fine tuning

Access description:

15CH	function	DMXvalue	describe
1	x-axis	0-255	
2	X axis fine tuning	0-255	
3	Y-axis	0-255	
4	Y-axis fine adjustment	0-255	
5	X Y axis velocity	0-255	Speed from fast to slow
6	Dyeing total dimming	0-255	Linear dimming from dark to bright

7	Dye stroboscopic	0-0	No function
		1-255	Synchronous stroboscopic speed from slow to fast (1HZ~25HZ)
8	R dimming	0-255	Red dimming from dark to bright
9	G dimming	0-255	Green dimming from dark to bright
10	B dimming	0-255	Blue dimming from dark to bright
11	W dimming	0-255	White dimming from dark to bright
12	electric rotating machinery	0-59	0-360 degree index
		60-119	The motor rotates clockwise from slow to fast
		120-179	The motor rotates counterclockwise from slow to fast
		180-255	The round-trip rotation of the motor is from slow to fast
13	Green Laser	0-255	Dimming from dark to bright
14	macro	0-49	Channel 1 to Channel 13 is valid
		50-149	Walksalf
		150-255	Lamp body sound control
15	reset	0-240	No function
		241-255	The lamp body is reset and 5 s is effective.