

Instruction manual

Space series · Space Seven

Thank you for choosing our space Seven lamps and lanterns, For your personal safety and better use of this product, Please read the manual carefully before using, Follow the procedure, To avoid misuse of personal safety damage and lamp damage.

一、 Packing list

After unpacking, Please check the product is qualified, Count all accessories. NO, please contact the distributor!

number	Name	Color	Unit	Quantity
1	Lamps and lanterns	Black	Station	1
2	Power Cord	Black	Ordinance	1
3	Handle	Black	PCS	1
4	Hexagon screws	Black	PCS	2
5	Instructions	Black and white	PCS	1

二、 Appearance and LED Function

Switch settings by pressing a button:

*Click “MENU” Key switch function.

*Click “UP/DOWN” Switch function or set address code.

*After switching functions, Click “ENTER” Key save function.



三、 Technical parameters

number	Category	Parameter
1	Power supply	AC95V-245V/50Hz
2	Product power	100W
3	Lamp beads	4 PCS 25 W lamp beads 1 PCS 50MW Red Laser 1 PCS 50MW Green Laser
4	Control	International DMX512, 14 channels
5	Mode of operation	DMX512, master/slave, self-walking, voice control
6	Dimming mode	0~100% ultra-smooth dimming
7	Strobe	20Time/second
8	Heat dissipation	Aluminum products cooling, forced cooling fan

四、DMX Channel function:

This product have 14 channels, Specific controls are as follows:

channels	Function	DMX Value	Description
1	X Motor	0-255	0~255 0-540 degree rotation
2	Y Motor	0-255	0~255 0-180 degree rotation
3	Y Motor Pulley	0-255	0-9 (none), 10-127 (forward rotation from slow to fast), 128-255 reverse rotation from fast to slow
4	XY Motor speed	0-255	0~255 from fast to slow
5	dimmer	0-255	Linear dimming from dark to light
6	Strobe	0-9	None
		10-255	form slow to fast
7	Red	0-255	Red Dimming from Dark to Light
8	Green	0-255	Green Dimming from Dark to Light
9	Blue	0-255	Blue Dimming from Dark to Light
10	White	0-255	White Dimming from Dark to Light
11	red laser	0-255	red dimmer 0-100
12	green laser	0-255	green dimmer 0-100
13	Macro function	0-50	Channels 1 through 12 are valid
		51-150	auto run
		150-255	voice autorun
14	reset	0-250	NONE
		251-255	reset after 3 second

Menu: A001-A512 Address Setting A 1-A 9 Self-propelled Mode S1 1-S1 9 Voice Control Mode Number Setting Voice Control Spirit Density Number Setting Voice Control Spirit Density Number Setting Voice Control Spirit Density Effect

五、Other parameters

number	Category	Parameters/details
1	Packaging	Standardized cartons
2	Size of inner box	34*27*24CM
3	Cartons	57*37*52CM
4	N.W	3.05KG
5	G.W	3.07KG
6	Carton weight	15.8KG
7	Power connection	Power Cord
8	Signal connection	Signal input line/output line
9	Material	Product materials: Ferrous, The shell: ABS

六、Maintenance

Do not stare at the luminescent body for a long time, It hurts the eyes;

Clean regularly Lens Keep the brightness and Extension Lamps and lanterns Service life.