

## 07-13 Chevy Silverado GMC Sierra Tow Mirrors Installing & Wiring Diagram

## 1. Screws location

- 1.1. Two kinds of door trim.
- 1.2. Remove three 10mm bolts




- 1.3. Remove door handle and plastic cover.
- 1.4. Remove five 10mm bolts.



## 2. Wiring Diagram

- 2.1. For models with power fold and puddle light functions, connect the mirror plug on the back of mirror switch panel.
- 2.2. For models without power fold function, connect the mirror plug on the female connector on door harness.
- 2.3. Main Plug (Rear View)



- (1)2)6 Mirror Motor
- ③ Mirror Heater
- 4 Not Used
- (5) LED Signal Light
- 7 Mirror Heater
- (8)9 Not Used
- 10 Signal Ground

## 2.4. Small AUX Plug





Female Plug on Mirror Base

Male Plug on Harness

Ground (Black)

Spot Light (Purple)

- 2.5. Run the wires through the rubber tunnel between the door and body frame.
- 2.6. Connect the black wire to the ground pole on body frame.
- 2.7. Connect the spot light (purple) wire to the trailer backup spot in fuse block. (Find the mark: TRLR BCKUP)

