


R2001-S



1064 nm 3 Port Polarization-Insensitive Optical Circulator, 300 mW

The polarization insensitive optical circulator utilizes proprietary designs and metal bonding micro-optics packaging. It's a compact, high-performance component, with high isolation, low insertion loss, low PDL, high stability and reliability. It is widely used in metro area network, wavelength add/drop, bi-directional communication systems, dispersion compensation and optical amplifiers.

Passive
Devices

Passive
Devices

FEATURES

- Low Insertion Loss
- Wide Band High Isolation
- Low PDL
- High Stability and Reliability
- Compact In-Line Package
- Epoxy-free on Optical Path

USE IN

- Optical Amplifiers
- Metro Area Network
- Wavelength Add/Drop
- Dispersion Compensation
- Bi-Directional Communication

Grade	P
Operating Wavelength	1064±30 nm
Isolation Loss	50 dB typ.; 40 dB min.
Insertion Loss	0.6 dB typ.; 0.8 dB max.
Cross Talk	50 dB min.
Return Loss	50 dB min.
PDL	0.15 dB max.
Polarization Mode Dispersion	0.1 ps
Power Handling	300 mW
Operating Temperature	-10°C to +75°C
Fiber Type	Corning HI 1060 Fiber