

Detect DC,AC and pulse current, high insulation between primary side and the vice side circuit.

Change the connection mode of primary bus-bar can be converted into three measuring range.

### Product application

- Metallurgy
- Welding machine
- Robot
- Inverter power
- Inverter speed controller
- UPS uninterrupted power supply

### Product features

- Light weight
- Low power consumption
- No insertion loss
- Fast response time
- Small size and beautiful appearance
- PCB mounting and easy to use

Product picture printing is for reference only, subject to the actual product



Electrical parameters: the following parameters are typical values, the actual values shall be subject to the actual measurement of the product

Rated input	$\pm 6\text{A}$
Input measurement range	$\pm 9\text{A}$
Rated supply voltage	$+3.3\text{V}$
Rated output	$1.65\text{V}\pm 0.625\text{V}$
Accuracy	1%
Linearity	0.1%
Current consumption	$\leq 20\text{mA} + I_s$
Load impedance	$\geq 10\text{K}\Omega$
Zero offset voltage	$\leq \pm 15\text{mV}$
Response time	$\leq 0.5\mu\text{s}$
Weight	9g
Operation temperature	$-25^\circ\text{C} \sim +70^\circ\text{C}$
Storage temperature	$-25^\circ\text{C} \sim +70^\circ\text{C}$
Band width	DC~150KHz
Dielectric strength	3KV 50Hz 1min

Primary turns	Rated input (A)	Rated output (V)	Connection way of primary pins
1	$\pm 6$	$1.65 \pm 0.625$	IN 1 2 3 OUT 6 5 4
2	$\pm 3$	$1.65 \pm 0.625$	IN 1 2 3 OUT 6 5 4
3	$\pm 2$	$1.65 \pm 0.625$	IN 1 2 3 OUT 6 5 4

Calculation formula:  $1.65\text{V}\pm 0.625\text{V}$


Forward direction:  $1.65 + (I/I_{PN}) * 0.625$

Reverse direction:  $1.65 - (I/I_{PN}) * 0.625$


I: Actual measured current

$I_{PN}$ : Rated input current


### Wiring diagram:




### Dimensions (in mm $\pm 0.5$ ):



Front view



Side view



Bottom view