

### **SURGE PROTECTOR WITH 8** BN-LINK° OUTLETS 3 USB CHARGING PORTS

## BNC-60/U186

### **Function Description** - Dual functionality: Combination of USB charging port and outlets

- Wide Space & Double Stability
- Surge Protection with Indicator Lights
- With overload protected - Operating environment: for indoor use only



# Appearance

**Input & Output** 



AC Input: 125VAC 60Hz AC Output: 15A 1875W

USB Charging Ports:2 USB-A+1 USB-C

Surge Joule Rating:800J

Power Cable Length:5FT





Product Measurement (inch): 4.33×3.19×8.03

Product Weight (lb): 1.06

Unit Package Measurements (inch): 4.33×3.19×8.03

Unit Package Weight (lb): 1.18 Master Carton Measurements (inch): 22.44×14.65×16.85 Master Carton Weight (lbs): 49.55 Master Carton Quantity: 40 PCS Master Carton Cube (cu.ft): 3.21

BN-LINK INC. 11701 6th Street, Rancho Cucamonga, CA 91730 Customer Service Assistance: 1.909.592.1881 E-mail: support@bn-link.com