
CONNECTOR DATASHEET



GPO(SMP)(FEMALE)-GPO(SMP)(FEMALE)

JGPO-KK6



*Dimensions are in mm

Configuration		
Connector 1 Type	GPO(SMP) Female	
Connector 1 Impedance	50 Ohms	
Connector 1 Polarity	Standard	
Connector 2 Type	GPO(SMP) Female	
Connector 2 Impedance	50 Ohms	
Connector 2 Polarity	Standard	
Connector Mount Method	None	
Adapter Body Style	None	
Electrical Specificatio Frequency	DC to 18 GHz	
Insertion Loss(dB)		
Return loss/VSWR	\leq 0.1 \times Sqt.(f_GHz) 1.35 to 18GHz	
Return loss/VSWR	1.35 to 18GHz	
Return loss/VSWR	1.35 to 18GHz	
Return loss/VSWR Materials Information	1.35 to 18GHz	
Return loss/VSWR Materials Information Centre Contact	1.35 to 18GHz CuBe Gold Plated	
Return loss/VSWR Materials Information Centre Contact Outer Contact	1.35 to 18GHz CuBe Gold Plated CuBe Gold Plated	
Return loss/VSWR Materials Information Centre Contact Outer Contact Body	1.35 to 18GHz CuBe Gold Plated CuBe Gold Plated CuBe Gold Plated CuBe Gold Plated	
Return loss/VSWR Materials Information Centre Contact Outer Contact Body Dielectric	1.35 to 18GHz CuBe Gold Plated CuBe Gold Plated CuBe Gold Plated CuBe Gold Plated	

While the information has been carefully compiled to the best of our knowledge, nothing is intended as representation or warranty or our part and no statement herein shall be construed as recommendation to infringe existing patents. In the effort to improve ou products, we reserve the right to make changes judged to be necessary.

Gwave Technology, Inc.	Tel.: +1(888)251-2240	Page
12630 H Westminster Ave., Santa Ana, CA 92706	Fax: +1(714)988-4223	,
www.gwavetech.com	Email:sales@gwavetech.com	1 / 1