

















PROJECT NAME:	CAT. #:
NOTES:	FIXTURE SCHEDULE

# Plug & Play Network BLE Nodes & Sensors



#### ANT-5-4T-BLE

#### **Sharkward Overview**

The Sharkward Bluetooth Lighting Control provides automated individual and group control of light fixtures using on sensors and Bluetooth sigmesh technology.

The ANT-5-4T-BLE mounted in an Commercial lighting fixture and provides multi-level control solution based on motion and or daylight harvesting contribution.

### **Applications:**

- Car Parking
- Hospitals
- Schools
- Warehouses
- Industrial

#### **Features**

- Lighting controls meet design lights consortium (DLC) networked lighting control system technical requirements (Version NLC5 June 23, 2020).
- · Quicky connect and adjust different sensor angle.
- Easy commissioning with tuya/sharkward App (Available in IOS and Android).
- Bluetooth network with SaaS working by computer
- · Individual addressability and/or grouping.
- Time clock scheduling for individual lights, groups or scenes.
- Multi-level dimming: manual ON/OFF automatic ON/OFF, and automatic partial ON/OFF, daylight harvesting control capability.
- 5 Year Warranty

### **Microwave Sensor Features**

DAYLIGHT HARVESTING	ON/OFF
MOTION SENSING	ON/OFF
FIRST TIME DELAY	1-59 minutes/infinite
SECOND TIME DELAY	0-59 minutes/infinite
DIM LEVEL	0-100%
MOUNTING HEIGHT	13-40ft
DETECTION RANGE	Up to 52ft diameter
DETECTION HORIZONTAL PATTERN	360°
DETECTION VERTICAL PATTERN	90°

### **Ordering Information**

MODEL NUMBER	DESCRIPTION
ANT-5-4T-BLE	NETWORK NODE PLUG & PLAY, WHITE



5-year standard warranty (further details available at <a href="www.sharkward.com">www.sharkward.com</a>) Product may be eligible for a warranty extension to 10 years, for anadditional fee. Contact sharkward for details.

















PROJECT NAME:	CAT. #:
NOTES:	FIXTURE SCHEDULE:


# **Round Network BLE Nodes & Sensors**


Specifications:	ANT-5-4T-BLE
NETWORK BLE SIGMESH	Yes
DAYLIGHT HARVESTING	Yes
MICROWAVE MOTION SENSOR	Yes
DETECTION MODE	Occupancy/Vancancy/Bi-level in 1 Unit
OPERATING VOLTAGE	12-24V DC
OPERATING CURRENT	> 50mA
SINKING CURRENT	max. 25mA
CONTROL OUTPUT	0-10V
RADIO FREQUENCY	2.4GHz ± 75MHz
WIRELESS STANDARD	BLE 4.2 MESH IEEE 802.15.1
PROGRAMMING	Tuya/sharkward App mobile app(IOS and android) or SaaS
CYBERSECURITY	UL1376
ENCRYPTION	AES 128-bit
MESH RANGE	100ft node-to-node and 50ft node-to-device (Commissioning)
SAFETY	cULus Listed
FCC	FCC ID:2AVMOANT-5-X
OPERATING TEMPERATURE	-40°F ~ +158°F (-40°C ~ +70°C)
IP RATING	IP65
COLOR	White

<sup>\*</sup>Must be paired with a Network Wall Switch

### **Product Dimensions**

### ANT-5-4T-BLE







5-year standard warranty (further details available at <a href="www.sharkward.com">www.sharkward.com</a>) Product may be eligible for a warranty extension to 10 years, for anadditional fee. Contact sharkward for details.

Phone: +86 13306608076 Fax: 0574-87790863 E-mail: info@sharkward.com
















_		
•	5	
,	YEAR	


CAT. #: \_ PROJECT NAME: NOTES:\_ FIXTURE SCHEDULE:

## **Round Network BLE Nodes & Sensors**

## **Detection Coverage**

### ANT-5-4T-BLE





## Commissioning

Tuya/Sharkward mobile App makes it easy to pair devices, create groups, set scenes/schedules, customize dimming levels, and adjust high trim based on application needs.









5-year standard warranty (further details available at www.sharkward.com) Product may be eligible for a warranty extension to 10 years, for anadditional fee. Contact sharkward for details.