

Technical:

Voltage: AC110-240V 50/60HZ

Power: 40W

Light source: 127pcs *5050 3in1 LED

Channel: 8CH

Control model: DMX512, Auto, Sound, Master-slave
Point control

Size: 21*9*23cm

Weight: 0.7kg

LED Stage Lighting Operating Manual

Point Control Magic Par Light



User Manual

Menu description

Menu	Range	Function
A001	1-512	DMX512 address
ADYE	ADYE/ADNO	Turn on/off DMX512 first
Au01	1-7	Choose color
FF90	00-99	Jump change
EE90	00-99	Gradate change
CC90	00-99	Pulse change
F000	000-255	Strobe
Soud	Soud/Sund	Sound Strobe
Sund	Soud/Sund	Sound color changed
R255	000-255	Red brightness
G255	000-255	Green brightness
B255	000-255	Blue brightness
Eu01	01-22	Multi-function (single control function)
SP99	00-99	Multi-function speed control

Channel description

Channel	Range	Function
CH1	0-255	Total dimmer
CH2	0-255	Red
CH3	0-255	Green
CH4	0-255	Blue
CH5	0-255	Strobe
CH6	0-255	Macro function(RGB full color)
CH7	0-255	Multi-function (single control function)
CH8	0-255	Speed