

5370 Strobe	8CH	00--255	Strobe all dimmer	
	9CH	000-08	NO Strobe	
		009-255	Strobe from slow to fast	
	10CH	00--255	Strobe effect	
	11CH	00--255	Strobe effect from slow to fast	
LED spot	12CH	00--255	spot all dimmer	
	13CH	0-08	NO Strobe	
		009-255	Strobe from slow to fast	
	14CH	00-255	Color mix 1	
	15-16CH	
	17CH	00-255	Color mix4	
	18CH	00-255	Spot effect	
19CH	00-255	Spot effect from slow to fast		
laser	20CH	0-7 / 8-127	ON/OFF	Red
		128-255	ON&OFF cycle	
	21CH	0-7 / 8-127	ON/OFF	Green
		128-255	ON&OFF cycle	
	22CH	00-010	stop	
		011-120	Movement forward fast to slow	
		210--134	Stop	
		135--245	Movement forward Slow to Fast	
		246--255	Stop	
	23CH	000-007	No function	
		008--255	Show model for laser	
24CH	0-255	Laser effect from slow to fast		



User Manual

Multifunctions 5in1 effect light

Professional Entertainment Equipment

Features

Voltage: AC110-240V 50/60Hz

Power:100W

Light source: SMD5730LED + 81pcs with color 3w UV CREE single color
+Laser:R=100MW , G=70MW +Derby:5mm LED R16,G12,B12 ,W16

4operation modes: Automatic running, DMX, Sound Active, Master/Slave

Sound controlled via built-in microphone

0-100 linear dimmer, high power led and low power consumption

11CH/24CH DMX channels selectable

Packing Size:

Weight: 3.5 kgs

Control

Menu display Instruction

DMX address	ADDR	DMX address (0-512)	
Channel mode	CHND	11CH/ 24CH	
Master/Slave	SLNA	URST	Slave 1
			Slave 2
Sound mode	SOUN	Sound 0--sound 59	
		SENS 0--100	
AUTO	AUTO	AUTO 0--4	
		Speed 0--9	
LED	display	ON/OFF	
Display inversion	DISP	inversion	
Software version	Ver	V12	

DMX controller

11 CH Mode

Effect	Channel	DMX Value	Function
4in1 LED+UV	1CH	0-255	See show table mix color
	2CH	0-255	Mix color effect from slow to fast
	3CH	0-008	NO strobe
009-255		LED strobe from slow to fast	
5370 Strobe	4CH	0-255	See show table strobe SMD5370
	5CH	0-255	Strobe effect from slow to fast
	6CH	0-08	NO Strobe
009-255		Strobe from slow to fast	
LED spot	7CH	0-255	See show table spot effect
	8CH	0-255	Spot effect from slow to fact
	9CH	0-008	NO strobe
009-255		Strobe effect from slow to fast	
laser	10CH	000-007	No function
		008--255	Show model for laser
	11CH	0-255	Laser effect from slow to fast

24 CH Model

Effect	Channel	DMX Value	Function
4in1 LED+UV	1CH	0-255	All dimmer
	2CH	0--008	NO strobe
		009-255	LED strobe from slow to fast
	3CH	0-255	UV dimmer
	4CH	0-255	Color mix 1
	5CH	0-255	Color mix 2
	6CH	0-255	Color effect
7CH	0-255	Mix color effect from slow to fast	