

User Manual

Air Purifier

Before using your TOSOT Air Purifier please read this user manual in its entirety.

READ AND SAVE THESE INSTRUCTIONS

MODEL NUMBER

KJ350G

Table of Contents

Important Safety Instructions	01
Installation and Setup	01
Electrical Safety Warning	02
Specifications	04
Parts List	05
Operation	06
Installing the Filter	06
Connecting Power	07
Display and Control Panel	07
Cleaning and Maintenance	10
Troubleshooting	12
Warranty & Customer Support	13

Important Safety Instructions

Your safety and the safety of others is very important to us. Please read all instructions before use and save this user manual for future reference. A digital version can be obtained from Customer Support.

Installation and Setup



Only use your air purifier in an upright position. Make sure the angle of inclination<10°. Always place the appliance on a stable, flat, level surface to prevent the unit from overturning.



Place your air purifier in an area where it is NOT easily accessible to children. Children should be under supervision when they are near the unit.



Do not attempt to disassemble or repair any part of this appliance. All repairs and services must be performed by qualified service personnel.



Keep your air purifier away from fire. Do not store or use flammable gases or materials near the appliance.



Do not wash your air purifier in water. Keep the unit away from water, wet and damp areas. Never place in water or liquid.



Do not attempt to move your air purifier when it is powering on. Make sure the unit disconnects power before you start cleaning or servicing.



Do not sit, stand or rest hot or heavy objects on your air purifier.



Only for household use. Do not use the unit outdoors or for commercial use.



Keep plastic bags and sheets out of the reach of children as they might be mistakenly used for play. Packaging materials may pose a risk of suffocation if not disposed of properly.



Do not attempt to operate your air purifier if it visibly damaged, malfunctioning, disassembled or has missing or broken parts. This includes exposed wiring on a damaged cord or electrical plugin.

Electrical Safety Warning



- Always plug into a fixed 120V 60 Hz AC outlet.
- Your air purifier should be plugged directly into a power outlet. Power outlets should be properly rated, protected, and sized in order to avoid electrical overload.
- Do not use a multiplug power strip or extension cord. Failure to do so may result in short-circuit or electrical shock.
- Push the power plug all the way into the wall outlet so that it will not be loose.



- Do not damage, alter, excessively bend, twist, pull or heat the power cord.
- Do not cover the power cord with a rug or carpeting.



- Do not plug or unplug your air purifier with wet hands.
- Do not use your air purifier if the outlet is damaged or loose.



• To Reduce The Risk Of Fire Or Electric Shock, Do Not Use This Fan With Any Solid-State Speed Control Device.

• POLARIZED PLUG WARNING:



THIS APPLIANCE HAS A POLZRIZED PLUG. One blade is wider than the other. To reduce the risk of electric shock, this plug is intended to fit in a polarized outlet only one way. If the plug does not fit fully in the outlet, reverse the plug. If it still does not fit, contact a qualified electrician to install the proper outlet.

DO NOT ATTEMPT TO MODIFY THIS PLUG OR DEFECT THIS SAFETY FEATURE IN ANY WAY.



• Unplug or disconnect the appliance from the power supply before servicing.



• This product complies with the maximum allowable concentration of ozone of 0.050 parts per million by volume (ppmv) in a 24-hour period. The Health Canada Guideline 2010 recommends that the maximum exposure limit, based on an averaging time of 8 hours, is 0.020 ppmv or less when tested in a sealed, controlled room approximately 30 m³.



OZONE DENSITY about HEPA AIR PURIFIER

Specifications

Power Supply	AC120V, 60Hz (18AWG power cord)	
Standby Power	0.6W	
Rated Power	58W	
Operating TEMP	41~104°F (5~40°C)	
Filter Grade	H13 (TiO2 Treated)	
Dimension	10.5*12*23in (26.5*31*59cm)	
Weight	17.6lbs / 8kg	

Parts List



Operation

Installing the Filter

For safety concern, do not open the grille cover and replace filter when the unit powers on. Make sure the unit disconnects power before installing/replacing the filter.





- 3. Install the new filter and then place the front grille cover back in place.
- * Make sure the filter placed in the right position. Pull-tag on the filter should be outward and the white side with "True-HEPA" should be inward.



Connecting Power

- Always plug into a fixed 120V 60 Hz AC outlet.
- Do not force the polarized plug into the outlet. It will only fit one way.
- Do not plug or unplug your air purifier with wet hands.



Display and Control Panel





Controls:





- 13 Operation Mode & Speed Setting
- 14 On/Off Button



ON/OFF Button

Press to power the air purifier ON or OFF.



Operation Mode & Speed Setting

Press to cycle between operation mode and speed as it shows below: Sleep Mode->Low Speed->High Speed->Turbo Clean->Auto Mode





Sleep Mode

In sleep mode, your air purifier will run at the lowest noise level to keep it the quietest during your sleep cycle.

ふー やー か

Press to switch 3 level fan speeds

- Low Speed: Suitable for regular cleaning and for rooms with fewer people and less pollution.
- **High Speed:** Suitable for faster cleaning and removing airborne dust, smoke particles and pet dander.
- **Turbo Clean:** Suitable for rooms with relatively high polluted air quality such as heavy smoke, heavy dust or bad odor. Unit runs at the highest speed to clean air.



Auto Mode

In Auto mode, your air purifier will automatically adjust the speed according to the air quality level.

You would see the color changing of indicating the Air Quality level as below:

Indicator	Color	Air Quality
Image: A start of the start	Green	Good
Ð	Yellow	Medium
Ð	Red	Poor



Filter Reset

When the indicator lights on, it is a reminder for you to replace the filter, you should check if it needs to be cleaned or replaced.

(More maintenance details see page 9)



Timer Setting

- Press to activate the timer button, you could set time options (2H, 4H&8H) to adjust the length of the timer before the unit powers off.
- Your air purifier will automatically power off once the timer is finished.
- To exit the timer setting, continue tapping (2) until the light shuts off.





UV LED Light

Press to turn the UV LED Light **ON/OFF**.

This air purifier has a built-in long life LED UV Titanium Dioxide (TiO₂) technology system. When activated by the LED UV light, the TiO₂ can help enhance the elimination of airborne germs.

To activate the UV function, tap the UV control icon " (UV) " until the " UV " indicator is illuminated. To turn OFF the UV, tap until the UV indicator light shuts off.

You don't need to do the normal maintenance or replace the UV LED light.

Cleaning and Maintenance

Filter Replacement Tips:

- When the indicator () light is on, it is a reminder for you to check if the filter needs to be cleaned or replaced.
- The general life cycle for the filter is 6-8 months, which means you need to replace the filter every 6-8 months.
- If your air purifier is running in an environment of relatively high pollution, you may need to change the air filter more often.

Pay attention to the following alarm signals for the filter:

- Increased noise when the unit is running.
- Decreased airflow
- Clogged filters
- Increased presence of odors

How to replace the air filter?

- a. Unplug the air purifier before installation of the air filter.
- b. Push the left side " 🖗 " marked place, and then press the other side to open the front grille cover. Remove the used filters and replace with a new filter.
- * Use only TOSOT authorized air filter replacements for TOSOT KJ350G Air Purifier. Go to www.tosotdirect.com or contact our Customer Support for more information.



c. Install the new filter and then place the front grille cover back in place.



d. Power on the air purifier and reset the Filter Replace Reminder. Press the Filter Reset icon "()", holding for 3 seconds until the reminder indicator "()" turns OFF. This action is to recount the lifespan of the new filters.

Regular Cleaning Tips:

- Make sure your air purifier is disconnected from the power outlet before you start cleaning.
- Keep cleaning the front grille cover every 30 days after continuous operation. It can be rinsed or wiped with warm water. But make sure the grille cover is completely dry before installing it back into the outlet.
- To prevent water drops going inside of the unit, using only a dry cloth to wipe the air purifier body is recommended.

Long-Term Storage Checklist Tips:

- Disconnect unit from the power outlet.
- Remove the filter and store in plastic packing.
- Wrap the unit and store in a dry place.

Troubleshooting

Problem	Possible Cause	Solution
Air purifier not working	Unit is not connecting the power supply.	Plug in the power outlet.
	Filter or front grille cover not fully installed.	Reinstall the filter and the front grille cover, make sure they are in the proper place. (see page 6)
	The time set up to operation runs out.	Exist the timer setting mode.
Unusual noise	Not placing the unit on a stable and flat surface.	Place the unit on a hard, stable surface. Make sure the angle of inclination<10°
	Dirty Filter	Replace a new air filter (see page10)
	Abnormal noise from inside the machine	Stop use and contact Customer Support.
Bad smell from air outlet	Dirty filter with accumulated dust and contaminants.	Replace a new air filter (see page 10)
	Unit is running in an area with high humidity, which may slowly cause an accumulation of bacteria with a bad smell.	Make sure your unit does not run in an area with high humidity.

* If your problem is not listed, please contact Customer Support for more information.

Warranty & Customer Support

Warranty Information

1. 3-Year warranty:

TOSOT KJ350G Air Purifiers come with a **3-Year** warranty from the date of purchase. This warranty covers manufacturing and material defects. Please visit https://tosotdirect.com/warranty for more terms & policy.

2. Additional 6-Month warranty extension:

You can get a 6-month warranty extension by registering your new product at <u>www.tosotdirect.com/extend</u> and answering a short questionnaire.

Customer Support

Questions? We are here to help

support@tosotdirect.com
1-844-888-6768
www.tosotdirect.com



Share your experience



